

«First_Name» «Last_Name»

IP Phone & Voicemail

Quick Reference Guide

Phone Basics



Logging In	Making Calls	
	Primary Office	2-Digit Location + 4-Digit Extension
Username: Enter «PrimaryDID» Press OK. Password: Enter «PrimaryDN»99 Press OK.	Other Office	2-Digit Location + 4-Digit Extension
	Local & Toll Free*	9 + 10-Digit Phone Number
Logging Out	Long Distance*	9 + 10-Digit Phone Number
 Press Menu. Selection option 1. Logoff, press OK. Press Yes. 	International	9 + 011 + Country Code + City Code + Phone Number
	*Using 1 is Optional	

Basic Phone Features

Transferring Calls	Conferencing Calls	
Press Transfer key.	1. While on a call, press Conferenc key.	
2. Dial a number.	2. Dial the first number.	
3. When you hear ringing or someone answers, press Transfer	3. When someone answers, press Conferenc key.	
key again to connect the call.	Note: You can conference up to 6 people.	
Transferring Calls to Voicemail	Forwarding Calls	
1. Press Transfer key.	Press Up Navigation key to the second screen.	
Dial xxxx or press Express Msg key.	2. Press Forward key. (icon is activated)	
3. Dial the 6-Digit Extension of the person followed by #.	3. Dial an internal extension.	
4. Press Transfer key.	4. Press Forward key.	
Disabling Call Forward	Disconnecting a Call	
Press the Forward key. (icon is removed)	Press the Goodbye key.	

Advanced Phone Features

Viewing Incoming Call Logs	Viewing Outgoing Call Logs		
1. Press Shift/Inbox key.	Press Shift/Outbox key.		
Press Down Navigation key to scroll through the calls.	Press Down Navigation key to scroll through the calls.		
Answering a Second Call	Redial Last Number Dialed		
Press Line 2 key to answer the call.			
Note: You do not have to press the Hold key when switching between calls.	1. Press the # key twice.		

Notes



«First Name» «Last Name»

IP Phone & Voicemail

Quick Reference Guide

Advanced Phone Features (Continued)

Using the Directory Key

To Store a Number:

- 1. Press Directory key, select New Entry and Press OK.
- 2. Press OK at 1. Number, type in a number, Press OK.
- Press Down Navigation key to 2. Surname, Press OK, Type a person's last name, Press OK to accept.
- Press Down Navigation key to 3. First Name. Press OK. Type a person's first name, Press OK to accept.
- 5. Press Down Navigation Key to 5. Save. Press OK to save.

Note: Enter the number exactly how you would dial it, including a 9 or 1.

To Dial a Directory Contact:

- 1. Press Directory key.
- 2. Press Down Navigation key to select a Name.
- 3. Press Dial.

To Store a Number:

 Press Up Navigation key twice to reach the third page of your screen.

Using the Auto Dial Keys

- 2. Press Auto Dial key.
- 3. Enter a Phone Number and press Auto Dial key again.

To Label an Auto Dial Number:

- 1. Press Menu key.
- 2. Press Down Navigation key to 4. Feature. Press OK.
- 3. Press **Down Navigation** key until you reach the number you just programmed. Press **OK**.
- Press OK at 1. Label, and type in a label using your phone keypad. Press OK to accept.
- Press Cancel three times to exit.

Voicemail Basics

Voicemail Setup	Retrieving Voicemail	Voicemail Shortcuts
	Option 1: From your Desk	1 Listen to messages/ Rewind
 Pick up handset or press Handsfree key. 	Pick up handset or press Handsfree key.	3 Fast Forward
2. Press Voicemail key.	2. Press Voicemail key. 3. Enter your password + # key.	4 Reply to message
Enter your default password which is «PrimaryDN»99 followed by #.	Option 2: From Another Phone 1. Dial xxx.xxx.xxxx 2. Enter your 6-Digit Extension + # key. 3. Enter your password + # key.	5 Call message sender
Follow the operator instructions. Make sure to note your new password!		6 Forward message
		7 Delete message
		8 Play envelope information
New Password	Option 3: Calling Your Phone 1. Dial your 10-Digit Number.	9 Save message
	2. During the greeting, press *.	# Skip header/Skip to next message
	3. Enter your password + # key.	* Pause/resume

Other Information

Personal Agent		Unit	Unified Messaging IMAP Settings	
Website	http://C4Communicate.net	Account Type	IMAP	
Username	«EMail»	Your Name	«First_Name» «Last_Name»	
Password	«PrimaryDN»99	Email	«PrimaryDID»	
	Unified Messaging Portal	Incoming Server	um.c4voicemail.net	
Website	http://C4Voicemail.net	Outgoing Server	um.c4voicemail.net	
Username	«PrimaryDID»@domain.c4voicemail.net	Username	«PrimaryDID»@domain.c4voicemail.net	
Password	«PrimaryDN»99	Password	«PrimaryDN»99	
1	New Portal/IMAP Password:		•	

Notes