

## «First\_Name» «Last\_Name»

# IP Phone & Voicemail

## **Quick Reference Guide**

#### **Phone Basics**



| Logging In   | Making Calls         |  |
|--|----------------------|--|
|  | Primary Office       | 2-Digit Location + 4-Digit Extension                 |
| Username: Enter «PrimaryDID» Press OK.  Password: Enter «PrimaryDN»99 Press OK.                    | Other Office         | 2-Digit Location + 4-Digit Extension                 |
|  | Local & Toll Free*   | 9 + 10-Digit Phone Number                            |
| Logging Out  | Long Distance*       | 9 + 10-Digit Phone Number                            |
| <ol> <li>Press Menu.</li> <li>Selection option 1. Logoff, press OK.</li> <li>Press Yes.</li> </ol> | International        | 9 + 011 + Country Code + City<br>Code + Phone Number |
|  | *Using 1 is Optional |  |

#### **Basic Phone Features**

| Dasic Filotie Leatures   |   |  |  |  |
|--|---|--|--|--|
| Transferring Calls   | Conferencing Calls                              |  |  |  |
| 1. Press Transfer key.   | 1. While on a call, press <b>Conferenc</b> key. |  |  |  |
| 2. Dial a number.  | 2. Dial the first number.                       |  |  |  |
| 3. When you hear ringing or someone answers, press <b>Transfer</b> | 3. When someone answers, press Conferenc key.   |  |  |  |
| key again to connect the call.                                     | Note: You can conference up to 6 people.        |  |  |  |
| Transferring Calls to Voicemail                                    | Forwarding Calls                                |  |  |  |
| 1. Press <b>Transfer</b> key.                                      | Press Up Navigation key to the second screen.   |  |  |  |
| <ol><li>Dial xxxx or press Express Msg key.</li></ol>              | 2. Press Forward key. (icon is activated)       |  |  |  |
| 3. Dial the 6-Digit Extension of the person followed by #.         | 3. Dial an internal extension.                  |  |  |  |
| 4. Press Transfer key.   | 4. Press Forward key.                           |  |  |  |
| Disabling Call Forward   | Disconnecting a Call                            |  |  |  |
| Press the Forward key. (icon is removed)                           | Press the <b>Goodbye</b> key.                   |  |  |  |

#### **Advanced Phone Features**

| Viewing Incoming Call Logs                                 | Viewing Outgoing Call Logs                             |
|--|--|
| 1. Press Shift/Inbox key.                                  | Press Shift/Outbox key.                                |
| Press Down Navigation key to scroll through the calls.     | Press Down Navigation key to scroll through the calls. |
| Answering a Second Call                                    | Redial Last Number Dialed                              |
| Press Line 2 key to answer the call.                       |  |
| Note: You do not have to press the Hold key when switching | 1. Press the # key twice.                              |
| between calls.   |  |

### **Notes**



## «First\_Name» «Last\_Name»

# IP Phone & Voicemail

## **Quick Reference Guide**

## **Advanced Phone Features (Continued)**

## Using the Directory Key

#### To Store a Number:

- 1. Press Directory key, select New Entry and Press OK.
- 2. Press OK at 1. Number, type in a number, Press OK.
- Press Down Navigation key to 2. Surname, Press OK, Type a person's last name, Press OK to accept.
- Press Down Navigation key to 3. First Name. Press OK.
   Type a person's first name, Press OK to accept.
- 5. Press Down Navigation Key to 5. Save. Press OK to save.

**Note:** Enter the number exactly how you would dial it, including a 9 or 1

#### To Dial a Directory Contact:

- 1. Press Directory key.
- 2. Press Down Navigation key to select a Name.
- 3. Press Dial.

# Using the Auto Dial Keys To Store a Number:

- Press Up Navigation key twice to reach the third page of your screen.
- 2. Press Auto Dial key.
- 3. Enter a Phone Number and press Auto Dial key again.

#### To Label an Auto Dial Number:

- 1. Press Menu key.
- 2. Press Down Navigation key to 4. Feature. Press OK.
- 3. Press **Down Navigation** key until you reach the number you just programmed. Press **OK**.
- Press OK at 1. Label, and type in a label using your phone keypad. Press OK to accept.
- Press Cancel three times to exit.

#### **Voicemail Basics**

| Voicemail Setup   | Retrieving Voicemail   | Voicemail Shortcuts                |
|---|--|------------------------------------|
|   | Option 1: From your Desk   | 1 Listen to messages/ Rewind       |
| 1. Pick up handset or press <b>Handsfree</b> key.                                       | Pick up handset or press Handsfree key.  | 3 Fast Forward                     |
| 2. Press Voicemail key.   | 2. Press Voicemail key. 3. Enter your password + # key.  | 4 Reply to message                 |
| <ol><li>Enter your default password which is<br/>«PrimaryDN»99 followed by #.</li></ol> | Option 2: From Another Phone 1. Dial xxx.xxx.xxxx 2. Enter your 6-Digit Extension + # key. 3. Enter your password + # key. | 5 Call message sender              |
| Follow the operator instructions. Make sure to note your new password!                  |  | 6 Forward message                  |
|   |  | 7 Delete message                   |
|   |  | 8 Play envelope information        |
| New Password  | Option 3: Calling Your Phone 1. Dial your 10-Digit Number.   | 9 Save message                     |
|   | 2. During the greeting, press *. 3. Enter your password + # key.   | # Skip header/Skip to next message |
|   |  | * Pause/resume                     |

#### Other Information

|          | Personal Agent                      | Unit            | Unified Messaging IMAP Settings     |  |
|----------|-------------------------------------|-----------------|-------------------------------------|--|
| Website  | http://C4Communicate.net            | Account Type    | IMAP                                |  |
| Username | «EMail»                             | Your Name       | «First_Name» «Last_Name»            |  |
| Password | «PrimaryDN»99                       | Email           | «PrimaryDID»                        |  |
|          | Unified Messaging Portal            | Incoming Server | um.c4voicemail.net                  |  |
| Website  | http://C4Voicemail.net              | Outgoing Server | um.c4voicemail.net                  |  |
| Username | «PrimaryDID»@domain.c4voicemail.net | Username        | «PrimaryDID»@domain.c4voicemail.net |  |
| Password | «PrimaryDN»99                       | Password        | «PrimaryDN»99                       |  |
|          | New Portal/IMAP Password:           |                 | •                                   |  |

#### **Notes**